



General Support

Table of contents

Embedded DOCA Firmware Components

Supported NIC Firmware Versions

Embedded DOCA Drivers

DOCA Packages

Supported Host OS and Features per DOCA-Host Installation Profile

DOCA-OFED Version Interoperability

BF-Bundle (BFB) Version Upgrade/Downgrade

Supported DOCA Version Upgrade Using Standard Linux Tools on BlueField

API Changes

Device Definition

Unsupported Functionalities/Features/NICs

Embedded DOCA Firmware Components

Component	Version	Description
BlueField-3 NIC firmware	32.43.2402	Firmware is used to run user programs on the BlueField-3 which allow hardware to run
BlueField-2 NIC firmware	24.43.2402	Firmware is used to run user programs on the BlueField-2 which allow hardware to run
BMC firmware	<u>24.10-17</u>	BlueField BMC firmware
BlueField-3 eROT (Glacier)	00.02.0195 .0000	BlueField-3 eROT firmware
BlueField-2 eROT (CEC)	04.0f	BlueField-2 eROT firmware

Supported NIC Firmware Versions

 **Note**

DOCA 2.9.0 is the last DOCA release to support ConnectX-4. DOCA 2.9.0 will be an LTS version and will be supported for 3 years for bug fixes and CVE updates.

 **Note**

BlueField-2 and ConnectX-7 are the last generation of BlueField and ConnectX families, respectively, that are supported by MLNX_OFED.

Adapter Card	Bundled Firmware Version
--------------	--------------------------

BlueField-3	32.43.2026
BlueField-2	24.43.2026
ConnectX-7	28.43.2026
ConnectX-6 Lx	26.43.2026
ConnectX-6 Dx	22.43.2026
ConnectX-6	20.43.2026
ConnectX-5/ConnectX-5 Ex	16.35.4030
BlueField	18.33.1048
ConnectX-4 Lx	14.32.1900
ConnectX-4	12.28.2302

To obtain the official firmware versions, refer to the NVIDIA [Firmware Download](#) page.

Embedded DOCA Drivers

Component	Version	Description	Licenses
clusterkit	1.14.462-1.2410068	Multifaceted node assessment tool for high-performance clusters	BSD
collectx-clxapi	1.19.1	CollectX API library which allows any 3 rd party to easily use CollectX functionality in their own programs	Proprietary
dpacc	1.9.0-6	High-level compiler for the DPA processor which compiles code targeted for the data-path accelerator (DPA) processor into a device executable and generates a DPA program	Proprietary
dpcp	1.1.50-1.2410068	Provides a unified flexible interface for programming IB devices using DevX	Proprietary
flexio	24.10.2454	SDK which exposes an API for managing the device and executing native code over the DPA processor	Proprietary
fwctl	24.10.OFED.2 4.10.1.1.4.1	Subsystem designed to standardize the secure firmware interface for userspace, focusing on debugging, configuration, and provisioning	GPLv2

Component	Version	Description	Licenses
hcoll	4.8.3230-1.2410068	Contains support for building runtime configurable hierarchical collectives	Proprietary
ibarr	0.1.3-1.2410068	ip2gid address resolution and gid2lid path record resolution	GPL-2.0 with Linux-syscall-note or BSD-2-Clause
ibdump	6.0.0-1.2410068	Dump of InfiniBand traffic; diagnostic tool	BSD2+GPL2
ibsim	0.12-1.2410068	Open-source InfiniBand fabric simulator	GPLv2 or BSD
ibutils	2.1.1	ibdiagnet scans the fabric using directed route packets and extracts all the available information regarding its connectivity and devices.	Proprietary
ibutils2	2.1.1-0.21902.MLN X20241029.g 46cf6278.241 0068	Utilities for InfiniBand	Proprietary
iser	24.10.OFED.2 4.10.1.1.4.1	Storage related drivers	GPLv2
isert	24.10.OFED.2 4.10.1.1.4.1	Storage related drivers	GPLv2
kernel-mft	4.30.0-139	Kernel part of MFT tools (for firmware burning, etc.)	Dual BSD/GPL
knem	1.1.4.90mlnx3 - OFED.23.10.0.2.1.1	Open-source kernel module that enables high-perf intra-node MPI communication	BSD and GPLv2
libvma	<u>9.8.60-1</u>	Accelerates latency-sensitive and throughput-demanding TCP and UDP socket-based applications by offloading traffic from the user-space directly to the NIC or HCA	GPLv2 or BSD
libxlio	<u>3.40.2-1</u>	Boosts the performance of TCP/IP applications based on NGINX (CDN, DoH, etc.) and storage solutions as part of the SPDK	GPLv2 or BSD

Component	Version	Description	Licenses
mft	4.30.1-8	Set of firmware management and debug tools for NVIDIA devices	Proprietary
mlnx-dpdk	22.11.0-2410.1.0	Equivalent to DPDK upstream. The versioning of MLNX_DPDK indicates which upstream DPDK it is compatible with it (e.g., 22.11 is compatible with upstream DPDK 2022.11).	BSD, GPLv2, and GPLv2
mlnx-en	24.10-0.6.8.0.g9b1cc6c	Kernel drivers part for Ethernet-only package	GPLv2
mlnx-ethtool	6.9-1.2410068	Ethtool with optional MLNX adaptation	GPL
mlnx-iproute2	6.10.0-1.2410114	IPRoute with optional MLNX adaptation	GPL
mlnx-libsnap	1.6.0-2	Library designed to assist common tasks for applications wishing to interact with emulated hardware over BlueField and take the most advantage from hardware capabilities	Proprietary
mlnx-nfsrdma	24.10.OFED.2 4.10.1.1.4.1	Storage related driver for NFS over RDMA	GPLv2
mlnx-nvme	24.10.OFED.2 4.10.1.1.4.1	Storage related driver for NVMe	GPLv2
mlnx-ofa_kernel	24.10-OFED.24.10.0 6.8.1	Kernel drivers for Ethernet InfiniBand together	GPLv2
mlnx-snap	3.8.0-7	BlueField SNAP for NVMe and virtio-blk enables hardware-accelerated virtualization of local storage	Proprietary
mlnx-tools	24.10-0.2410068	Tools for loading modules, configurations, scripts, etc.	GPLv2 or BSD
mlx-regex	1.2-ubuntu1	Library providing RegEx pattern matching to DOCA applications using the regular expression processor (RXP) or software-based engines when required	Proprietary

Component	Version	Description	Licenses
mlx-steering-dump	1.0.0-0.2410068	Hardware/software steering dump parsing tools	GPLv2
mpiteststs	3.2.24-2ffc2d6.2410068	Test suite for benchmarking the MPI	BSD
mstflint	4.29.0-1	User space part of our MFT tools	GPL/BSD
multi-perf	3.0-3.0.2410068	Linux tool for perf testing	BSD 3-Clause, GPLv2 or later
ofed-scripts	24.10.OFED.2 4.10.1.1.4	Scripts used to build OFED	GPL/BSD
openmpi	4.1.7rc1-1.2410068	MPI implementation (for RDMA/RoCE) with some improvements done by the HPC team	BSD
opensm	<u>5.21.0.MLNX2</u> <u>0241126.d9a</u> <u>a3dff-</u> <u>0.1.2410114</u>	InfiniBand Subnet Manager and Subnet Administrator based on OpenSM	GPLv2 or BSD
openvswitch	2.17.8-1.2410068	OVS (virtual switch), DPDK based	ASL 2.0, LGPLv2+, and SISSL
perftest	24.10.0-0.65.g9093bae.2410068	Test suite for performance	BSD 3-Clause, GPLv2, or later
rdma-core	2410mlnx54-1.2410068	Implementation of the RDMA verbs	GPLv2 or BSD
rivermax	1:1.60.6	Optimized networking SDK for media and data streaming applications	Proprietary
rshim	2.1.8	User-space driver to access the BlueField SoC via the RShim interface, providing ways to push boot stream, debug the target, or login via the virtual console or network interface	GPLv2

Component	Version	Description	Licenses
sharp	3.9.0.MLNX20 241029.7a20 b607- 1.2410068	Improves the performance of MPI and machine learning collective operation by offloading from CPUs and GPUs to the network and eliminating the need to send data multiple times between endpoints	Proprietary
sockperf	3.10- 0.git5ebd327 da983.24100 68	Network benchmarking utility over socket API UDP/TCP designed for testing network performance (latency and throughput)	BSD
spdk	23.01.5-26	Provides a set of tools and libraries for writing high performance, scalable, user-mode storage applications	Proprietary
srp	24.10.OFED.2 4.10.1.1.4.1	Storage-related driver for SCSI RDMA Protocol initiator	GPLv2
ucx	1.18.0- 1.2410068	High-level application-oriented API for high-performance communication over RDMA networks	BSD
virtio-net-controller	24.10.30	Systemd service running on BlueField with a user interface front-end to manage the emulated virtio-net devices	Proprietary
xpmem	2.7.4- 1.2410068	Kernel module to enable inter-process mapping for memory copy in user space	GPLv2 and LGPLv2.1
xpmem-lib	2.7- 0.2310055	High-performance inter-process memory sharing	LGPLv2.1

DOCA Packages

Device	Component	Version	Description
Host	DOCA Devel	2.9.1	Software development kit package and tools for developing host software
	DOCA Runtime	2.9.1	Runtime libraries and tools required to run DOCA-based software applications on host

Device	Component	Version	Description
	DOCA Extra	2.9.1	Contains helper scripts (doca-info, doca-kernel-support)
	DOCA OFED	2.9.1	Software stack which operates across all NVIDIA network adapter solutions
Target BlueField DPU (Arm)	BlueField BSP	4.9.1	BlueField image and firmware
	DOCA SDK	2.9.1	Software development kit packages and tools for developing Arm software
	DOCA Runtime	2.9.1	Runtime libraries and tools required to run DOCA-based software applications on Arm

Supported Host OS and Features per DOCA-Host Installation Profile

The default operating system included with the BlueField Bundle (for DPU and SuperNIC) is Ubuntu 22.04.

The supported operating systems on the host machine per DOCA-Host installation profile are the following:

Note

Only the following generic kernel versions are supported for DOCA local repo package for host installation.

Operating System	Architecture	Default Kernel Version (Primary)/Tested with Kernel	Supported DOCA Profile	OS Support Model	ASAP 2 OVS-Kernel SR-IOV	ASAP 2 OVS-DPD K SR-IOV	NFS - over RD MA	N V M e	GPU Direct Storage (GDS)	UCX - CU DA Version

		Version (Community)										
			d oc a- all	doc a- net wor kin g	do ca - of ed	do ca - ro ce						
Alinu x 3.2	x8 6	5.10.134- 13.al8.x86_64	✓	✓	✓	✗	Primary	✗	✗	✗	✗	✗
Alma 8.5	x8 6	4.18.0- 348.12.2.EL8_ 5.X86_64	✗	✗	✓	✗	Community	✗	✗	✗	✗	✗
Anolis OS 8.4	aar ch 64	4.18.0- 348.2.1.AN8_ 4.aarch64	✗	✗	✓	✗	Community	✗	✗	✗	✗	✗
	x8 6	4.18.0- 305.AN8.X86_ 64	✗	✗	✓	✗	Community	✗	✗	✗	✗	✗
Anolis OS 8.6	aar ch 64	5.10.134+	✗	✗	✓	✗	Primary	✗	✗	✗	✗	✗
	x8 6	5.10.134+	✗	✗	✓	✗	Primary	✗	✗	✗	✗	✗
Azur e Linu x 3.0	x8 6	6.6.35.1- 5.azl3	✓	✓	✓	✗	Primary	✗	✗	✗	✗	✗

BCLinux 21.1 OSP 2	aarch64	4.19.90-2107.6.0.009 8.oe1.bclinux.aarch64						Primary				
	x86	4.19.90-2107.6.0.010 0.oe1.bclinux.x86_64						Primary				
BCLinux 22.1 0	aarch64	5.10.0-153.24.0.100. 6.oe2203sp2.bclinux.aarch64						Primary				
	x86	5.10.0-153.24.0.100. 6.oe2203sp2.bclinux.x86_64						Primary				
CentOS Stream 8	aarch64	4.18.0-552.EL8.AAR CH64						Community				
	x86	4.18.0-552.el8.x86_64						Community				
CentOS Stream 9	aarch64	5.14.0-480.EL9.AAR CH64						Community				
	x86	5.14.0-480.el9.x86_64						Community				
CTyun	aar	4.19.90-						Prim				

nOS	ch 64	2102.2.0.006 6.ctl2.aarch64						ary						
6	x8 6	4.19.90- 2102.2.0.006 6.ctl2.x86_64						Prim ary						
	aar ch 64	5.10.0- 136.12.086.ct l3.aarch64						Prim ary						
CTy nOS 23.0 1	x8 6	5.10.0- 136.12.086.ct l3.x86_64						Prim ary						
	aar ch 64	4.19.0-14- arm64						Prim ary						
Debi an 10.8	x8 6	4.19.0-14- amd64						Prim ary						
	x8 6	4.19.0-14- amd64						Prim ary						
Debi an 10.9	x8 6	4.19.0-16- amd64						Prim ary						
	x8 6	4.19.0-21- arm64						Prim ary						
Debi an 10.1 3	aar ch 64	4.19.0-21- arm64						Prim ary						
	x8 6	4.19.0-21- amd64						Prim ary						
Debi	aar	5.10.0-13-						Prim						

an 11.3	ch 64	arm64					ary						
	x8 6	5.10.0-13- amd64					Prim ary						
Debi an 12.1	aar ch 64	6.1.0-10- arm64					Prim ary						
	x8 6	6.1.0-10- amd64					Prim ary						
Debi an 12.5	aar ch 64	6.1.0-18- arm64					Prim ary						
	x8 6	6.1.0-18- amd64					Prim ary						
Euler OS 2.0 SP9	aar ch 64	4.19.90- vhulk2006.2.0 .h171.euleros v2r9.aarch64					Com mu nity						
	x8 6	4.18.0- 147.5.1.0.h26 9.eulerosv2r9. x86_64					Com mu nity						
Euler OS 2.0 SP1 0	aar ch 64	4.19.90- vhulk2110.1.0 .h860.euleros v2r10.aarch6 4					Com mu nity						

	x86	4.18.0-147.5.2.4.h69 4.eulerosv2r1 0.x86_64	(X) (X) (✓) (X)	Community	(X) (X) (X) (X) (X) (X)
Euler OS 2.0 SP1	aarch64	5.10.0-60.18.0.50.h3 23.eulerosv2r11.aarch64	(X) (X) (✓) (X)	Primary	(X) (X) (X) (X) (X) (X)
	x86	5.10.0-60.18.0.50.h3 23.eulerosv2r11.x86_64	(X) (X) (✓) (X)	Primary	(X) (X) (X) (X) (X) (X)
Euler OS 2.0 SP1	aarch64	5.10.0-136.12.0.86.h1032.eulerosv2r12.aarch64	(X) (X) (✓) (X)	Primary	(X) (X) (X) (X) (X) (X)
	x86	5.10.0-136.12.0.86.h1032.eulerosv2r12.x86_64	(X) (X) (✓) (X)	Primary	(X) (X) (X) (X) (X) (X)
Kylin 10 SP2	aarch64	4.19.90-24.4.v2101.ky10.aarch64	(X) (X) (✓) (X)	Primary	(X) (X) (X) (X) (X) (X)
	x86	4.19.90-24.4.v2101.ky10.x86_64	(X) (X) (✓) (X)	Primary	(✓) (X) (X) (X) (X) (X)
Kylin 10 SP3	aarch64	4.19.90-52.22.v2207.ky10.aarch64	(X) (X) (✓) (X)	Primary	(✓) (X) (X) (X) (X) (X)
	x86	4.19.90-		Primary	

		52.22.v2207.k y10.x86_64	(x)	(x)	(✓)	(x)	(✓)	(x)	(x)	(x)	(x)	(x)
Linu x	aar ch 64	6.11	(x)	(x)	(✓)	(x)	Primary	(✓)	(x)	(x)	(✓)	(x)
Kern el 6.11	x8 6		(x)	(x)	(✓)	(x)	Primary	(✓)	(x)	(✓)	(✓)	(x)
Mari ner 2.0	x8 6	5.15.148.2- 2.cm2	(x)	(x)	(✓)	(x)	Primary	(x)	(x)	(x)	(x)	(x)
Orac le Linu x 7.9	x8 6	5.4.17- 2011.6.2.el7u ek.x86_64	(x)	(x)	(✓)	(x)	Primary	(x)	(x)	(x)	(x)	(x)
Orac le Linu x 8.4	x8 6	5.4.17- 2102.2013.el 8uek.x86_64	(x)	(x)	(✓)	(x)	Primary	(x)	(x)	(x)	(x)	(x)
Orac le Linu x 8.6	x8 6	5.4.17- 2136.307.3.1. el8uek.x86_6 4	(x)	(x)	(✓)	(x)	Primary	(x)	(x)	(x)	(x)	(x)
Orac le Linu x 8.7	x8 6	5.15.0- 3.60.5.1.el8ue k.x86_64	(✓)	(✓)	(✓)	(x)	Primary	(x)	(x)	(x)	(x)	(x)
Orac le Linu x 8.8	x8 6	5.15.0- 101.103.2.1.el 8uek.x86_64	(x)	(x)	(✓)	(x)	Primary	(x)	(x)	(x)	(x)	(x)

Oracle Linux 9.1	x86	5.15.0-3.60.5.1.el9uek.x86_64				Primary	✗	✗	✗	✗	✗	✗	✗
Oracle Linux 9.2	x86	5.15.0-101.103.2.1.el9uek.x86_64				Primary	✗	✗	✗	✗	✗	✗	✗
OpenSUSE 15.3	aarch64	-				Community	✗	✗	✗	✗	✗	✗	✗
	x86	5.3.18-150300.59.43-DEFAULT				Community	✗	✗	✗	✗	✗	✗	✗
openEuler 20.03 SP1	aarch64	4.19.90-2012.4.0.0053.0E1.aarch64				Community	✗	✗	✗	✗	✗	✗	✗
	x86	4.19.90-2110.8.0.0119.0E1.X86_64				Community	✗	✗	✗	✗	✗	✗	✗
openEuler 20.03 SP3	aarch64	4.19.90-2112.8.0.0131.oe1.aarch64				Primary	✗	✗	✗	✗	✗	✗	✗
	x86	4.19.90-2112.8.0.0131.oe1.x86_64				Primary	✗	✗	✗	✗	✗	✗	✗
openEuler 22.0	x86	5.10.0-136.12.0.86.0e2203sp1.x86_64				Primary	✗	✗	✗	✗	✗	✗	✗

3 SP1												
open Euler 22.0 3 SP3	x8 6	5.10.0- 182.0.0.95.oe 2203sp3.x86_ 64	✓	✗	✓	✗	Primary	✗	✗	✗	✗	✗
Phot on OS 3.0	x8 6	4.19.225- 3.ph3	✗	✗	✓	✗	Community	✗	✗	✗	✗	✗
RHE L/Ce ntOS 8.0	aar ch 64 4	4.18.0- 80.el8.aarch6	✗	✗	✓	✗	Primary	✓	✓	✗	✗	✓
RHE L/Ce ntOS 8.0	x8 6	4.18.0- 80.el8.x86_64	✗	✗	✓	✗	Primary	✓	✓	✗	✗	✓
RHE L/Ce ntOS 8.1	aar ch 64 64	4.18.0- 147.el8.aarch	✗	✗	✓	✗	Primary	✓	✓	✗	✗	✓
RHE L/Ce ntOS 8.1	x8 6	4.18.0- 147.el8.x86_6 4	✗	✗	✓	✗	Primary	✓	✓	✗	✗	✓
RHE L/Ce ntOS 8.2	aar ch 64 64	4.18.0- 193.el8.aarch	✗	✗	✓	✗	Primary	✓	✓	✗	✓	✓
RHE L/Ce ntOS 8.2	x8 6	4.18.0- 193.el8.x86_6 4	✓	✓	✓	✗	Primary	✓	✓	✓	✓	✓
RHE L/Ce	aar	4.18.0-					Primary					12.6

ntOS 8.3	ch 64	240.el8.aarch 64	(x) (x) (✓) (x)	(✓) (✓) (x) (x)										
	x8 6	4.18.0- 240.el8.x86_6 4	(x) (x) (✓) (x)		Primary	(✓) (✓) (x) (x)								12.6
RHE L/Ce ntOS 8.4	aar ch 64	4.18.0- 305.el8.aarch 64	(x) (x) (✓) (x)		Primary	(✓) (✓) (x) (✓)								12.6
	x8 6	4.18.0- 305.el8.x86_6 4	(x) (x) (✓) (x)		Primary	(✓) (✓) (✓) (✓)								12.6
	aar ch 64	4.18.0- 348.el8.aarch 64	(x) (x) (✓) (x)		Primary	(✓) (✓) (x) (✓)								12.6
	x8 6	4.18.0- 348.el8.x86_6 4	(x) (x) (✓) (x)		Primary	(✓) (✓) (✓) (✓)								12.6
RHE L/Ce ntOS 8.5	aar ch 64	4.18.0- aarch64.18.0- 372.41.1.el8_6.aarch64	(x) (x) (✓) (x)		Primary	(✓) (✓) (x) (✓)								12.6
	x8 6	4.18.0- 372.41.1.el8_6.ppc64le	(x) (x) (✓) (x)		Primary	(✓) (✓) (x) (✓)								12.6
	pp c6 4le	4.18.0- 372.41.1.el8_6.x86_64	(✓) (✓) (✓) (x)		Primary	(✓) (✓) (✓) (✓)								12.6
	x8 6	4.18.0- 372.41.1.el8_6.x86_64	(✓) (✓) (✓) (x)		Primary	(✓) (✓) (✓) (✓)								12.6
RHE L/Ro cky 8.7	aar ch 64	4.18.0- 425.14.1.el8_7.aarch64	(x) (x) (✓) (x)		Primary	(✓) (x) (x) (✓)								12.6

	x86	4.18.0-425.14.1.el8_7.x86_64	(x) (x) (✓) (x)	Primary	(✓) (x) (✓) (✓) (✓)	12.6
RHE L/Rocky 8.8	aarch64	4.18.0-477.10.1.el8_8.aarch64	(✓) (✓) (✓) (x)	Primary	(✓) (x) (x) (✓) (✓)	12.6
	ppc64le	4.18.0-477.10.1.el8_8.ppc64le	(x) (x) (✓) (x)	Primary	(✓) (x) (x) (✓) (✓)	12.6
	x86	4.18.0-477.10.1.el8_8.x86_64	(✓) (✓) (✓) (✓)	Primary	(✓) (x) (✓) (✓) (✓)	12.6
RHE L/Rocky 8.9	aarch64	4.18.0-513.5.1.el8_9.aarch64	(✓) (✓) (✓) (x)	Primary	(✓) (x) (x) (✓) (✓)	12.6
	ppc64le	4.18.0-513.5.1.el8_9.ppc64le	(x) (x) (✓) (x)	Primary	(✓) (x) (x) (✓) (✓)	12.6
	x86	4.18.0-513.5.1.el8_9.x86_64	(✓) (✓) (✓) (✓)	Primary	(✓) (x) (✓) (✓) (✓)	12.6
RHE L/Rocky 8.10	aarch64	4.18.0-553.el8_10.aarch64	(✓) (✓) (✓) (x)	Primary	(✓) (x) (x) (✓) (✓)	12.6
	ppc64le	4.18.0-553.el8_10.ppc64le	(x) (x) (✓) (x)	Primary	(✓) (x) (x) (✓) (✓)	12.6
	x86	4.18.0-	(✓) (✓) (✓) (✓)	Primary	(✓) (x) (✓) (✓) (✓)	12.6

		553.el8_10.x8 6_64																	
RHE L/Rocky 9.0	aarch64	5.14.0-70.46.1.el9_0.aarch64	✗	✗	✓	✗	Primary	✓	✗	✗	✓	✓	12.6						
	ppc64le	5.14.0-70.46.1.el9_0.ppc64le	✗	✗	✓	✗	Primary	✓	✗	✗	✓	✓	12.6						
	x86_64	5.14.0-70.46.1.el9_0.x86_64	✗	✗	✓	✗	Primary	✓	✗	✓	✓	✓	12.6						
RHE L/Rocky 9.1	aarch64	5.14.0-162.19.1.el9_1.aarch64	✗	✗	✓	✗	Primary	✓	✗	✗	✓	✓	12.6						
	x86_64	5.14.0-162.19.1.el9_1.x86_64	✓	✓	✓	✗	Primary	✓	✗	✓	✓	✓	12.6						
RHE L/Rocky 9.2	aarch64	5.14.0-284.11.1.el9_2.aarch64	✗	✗	✓	✗	Primary	✓	✗	✗	✓	✓	12.6						
	ppc64le	5.14.0-284.11.1.el9_2.ppc64le	✗	✗	✓	✗	Primary	✓	✗	✗	✓	✓	12.6						
	x86_64	5.14.0-284.11.1.el9_2.x86_64	✗	✗	✓	✓	Primary	✓	✗	✓	✓	✓	12.6						
RHE L/Rocky 9.3	aarch64	5.14.0-362.8.1.el9_3.aarch64	✗	✗	✓	✗	Primary	✓	✗	✓	✓	✓	12.6						

	pp c6 4le	5.14.0- 362.8.1.el9_3. ppc64le						Primary							12.6
	x8 6	5.14.0- 362.8.1.el9_3. x86_64						Primary							12.6
	aar ch 64	5.14.0- 427.13.1.el9_ 4.aarch64						Primary							12.6
RHE L/Ro cky 9.4	pp c6 4le	5.14.0- 427.13.1.el9_ 4.ppc64le						Primary							12.6
	x8 6	5.14.0- 427.13.1.el9_ 4.x86_64						Primary							12.6
RHE L/Ro cky 9.5	aar ch 64	5.14.0- 503.11.1.el9_ 5.aarch64						Primary							12.6
	pp c6 4le	5.14.0- 503.11.1.el9_ 5.ppc64le						Primary							12.6
	x8 6	5.14.0- 503.11.1.el9_ 5.x86_64						Primary							12.6
SLES 15 SP2	aar ch 64	5.3.18-22- default						Primary							
	pp c6 4le	5.3.18-22- default						Primary							
	x8	5.3.18-22-						Prim							

	6	default											
SLES 15 SP3	aarch64	5.3.18-57-default											
	ppc64le	5.3.18-57-default											
	x86	5.3.18-57-default											
	aarch64	5.14.21-150400.22-default											
	ppc64le	5.14.21-150400.22-default											
	x86	5.14.21-150400.22-default											
	aarch64	5.14.21-150500.53-default											
	ppc64le	5.14.21-150500.53-default											
	x86	5.14.21-150500.53-default											
SLES	aar	6.4.0-											

15 SP6	ch64	150600.21-default						ary						
	ppc64le	6.4.0-150600.21-default						Prim ary						
	x86	6.4.0-150600.21-default						Prim ary						
TencentOS 3.3	aarch64	5.4.119-19.0009.39						Prim ary						
	x86	5.4.119-19.0009.39						Prim ary						
	aarch64	5.4.0-26-generic						Prim ary						12.6
Ubuntu 20.04	ppc64le	5.4.0-26-generic						Prim ary						12.6
	x86	5.4.0-26-generic						Prim ary						12.6
	aarch64	5.15.0-25-generic						Prim ary						12.6
Ubuntu 22.04	ppc64le	5.15.0-25-generic						Prim ary						12.6

	x8 6	5.15.0-25- generic	✓	✓	✓	✓	Primary	✓	✓	✓	✓	✓
Ubu ntu 24.0 4	aar ch 64	6.8.0-31- generic	✓	✓	✓	✗	Primary	✓	✓	✓	✓	✓
	pp c6 4le	6.8.0-31- generic	✗	✗	✓	✗	Primary	✓	✓	✓	✓	✓
	x8 6	6.8.0-31- generic	✓	✓	✓	✓	Primary	✓	✓	✓	✓	✓
	x8 6	6.11.0-8- generic	✗	✗	✓	✗	Primary	✓	✓	✓	✓	✓
UOS 20.1 060	aar ch 64	5.10.0- 46.uel20.aarc h64	✗	✗	✓	✗	Primary	✗	✗	✗	✗	✗
	x8 6	5.10.0- 46.uel20.x86_ 64	✗	✗	✓	✗	Primary	✗	✗	✗	✗	✗
	aar ch 64	5.10.0- 46.uelc20.aar ch64	✗	✗	✓	✗	Primary	✗	✗	✗	✗	✗
	x8 6	5.10.0- 46.uelc20.x86 _64	✗	✗	✓	✗	Primary	✗	✗	✗	✗	✗

DOCA-OFED Version Interoperability

This section reflects which versions were tested and verified for multi-version environments (i.e., environments with more than one doca-ofed version on host servers).

Target Version	Versions Verified for Interoperability
24.10 Oct 2024	24.07-0.6.1.0- DOCA-OFED Profile-2.8.0
	23.10-3.2.2.0 LTS-DOCA-OFED-2.5.2

BF-Bundle (BFB) Version Upgrade/Downgrade

The following table provides a matrix for the supported upgrade/downgrade of BFBs across different versions.

Version	Upgrade to	Downgrade to
1.5.0	2.0.2; 2.2.0; 1.5.1; 1.5.2; 1.5.3	1.4.0; 1.3.0
1.5.1	1.5.2	1.5.0
1.5.2	1.5.3	1.5.1; 1.5.0
1.5.3	N/A	1.5.2; 1.5.0
2.0.2	2.2.0; 2.5.0	1.5.0; 1.4.0
2.2.0	2.5.0; 2.6.0	N/A
2.2.1	2.5.0; 2.6.0	N/A
2.5.0	2.5.1; 2.6.0	2.2.1 for BlueField-3; 2.2.0 for BlueField-2
2.5.1	2.5.2	2.5.0
2.5.2	2.6.0; 2.7.0; 2.8.0; 2.9.0	2.5.1; 2.5.0
2.6.0	2.7.0; 2.8.0	2.5.0; 2.2.1 for BlueField-3; 2.2.0 for BlueField-2
2.7.0	2.8.0; 2.9.0	2.6.0; 2.5.0; 2.2.1 for BlueField-3; 2.2.0 for BlueField-2
2.8.0	2.9.0	2.7.0; 2.6.0; 2.5.0
2.9.0	2.9.1	2.8.0; 2.7.0
2.9.1	N/A	2.9.0; 2.8.0; 2.7.0

Supported DOCA Version Upgrade Using Standard Linux Tools on BlueField

Version	Upgrade to
2.5.0	2.5.1; 2.6.0; 2.7.0; 2.8.0
2.5.1	2.5.2
2.5.2	N/A
2.6.0	2.7.0; 2.8.0
2.7.0	2.8.0; 2.9.0
2.8.0	2.9.0
2.9.0	2.9.1
2.9.1	N/A

API Changes

N/A

Device Definition

The supported adapter cards are specified as follows:

Supported Cards	Description
All HCAs	Supported in the following adapter cards unless specifically stated otherwise: ConnectX-4/ConnectX-4 Lx/ConnectX-5/ConnectX-6/ConnectX-6 Dx/ConnectX-6 Lx/ConnectX-7/BlueField-2/BlueField-3
ConnectX-6 Dx and above	Supported in the following adapter cards unless specifically stated otherwise: ConnectX-6 Dx/ConnectX-6 Lx/ConnectX-7/BlueField-2/BlueField-3
ConnectX-6 and above	Supported in the following adapter cards unless specifically stated otherwise: ConnectX-6/ConnectX-6 Dx/ConnectX-6 Lx/ConnectX-7/BlueField-2/BlueField-3

Supported Cards	Description
ConnectX-5 and above	Supported in the following adapter cards unless specifically stated otherwise: ConnectX-5/ConnectX-6/ConnectX-6 Dx/ConnectX-6 Lx/ConnectX-7/BlueField-2/BlueField-3
ConnectX-4 and above	Supported in the following adapter cards unless specifically stated otherwise: ConnectX-4/ConnectX-4 Lx/ConnectX-5/ConnectX-6/ConnectX-6 Dx/ConnectX-6 Lx/ConnectX-7/BlueField-2/BlueField-3

Unsupported Functionalities/Features/NICs

The following are the unsupported functionalities/features/NICs in the current version:

- RDMA experimental verbs library (mlnx_lib)
- Common internet file system (CIFS) module installation
- Relational database service (RDS)
- mthca InfiniBand driver
- Ethernet IPoIB (eIPoIB)
- InfiniBand-connected transport service
- IPSec over bond for crypto offload

Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation ("NVIDIA") makes no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no

representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms of Sale for the product.

Trademarks
NVIDIA and the NVIDIA logo are trademarks and/or registered trademarks of NVIDIA Corporation in the U.S. and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

© Copyright 2024, NVIDIA. PDF Generated on 01/14/2025